1601/105 1602/105 ELECTRICAL AND SOLAR INSTALLATION TECHNOLOGY Oct./Nov. 2017 Time: 3 hours



THE KENYA NATIONAL EXAMINATIONS COUNCIL

CRAFT CERTIFICATE IN ELECTRICAL AND ELECTRONICS ENGINEERING

MODULE I

ELECTRICAL AND SOLAR INSTALLATION TECHNOLOGY

3 hours

INSTRUCTIONS TO CANDIDATES

You should have the following for this examination:

Answer booklet:

Drawing instruments;

This paper consists of TWO sections; A and B.

Answer any THREE questions from section A and any TWO questions from section B.

Maximum marks to each part of a question are indicated.

All dimensions are in millimeters.

Candidates should answer the questions in English.

This paper consists of 4 printed pages.

Candidates should check the question paper to ascertain that all the pages are printed as indicated and that no questions are missing.

© 2017 The Kenya National Examinations Council

Turn over

SECTION A

Answer THREE questions from this section.

Define the term 'final circuit'. (i) (a) Explain four IEE regulations requirements regarding final circuits. (6 marks) (ii) Draw the wiring diagram for a final circuit serving. (b) 3 lights each controlled by a single pole switch using ceiling-rose method. (i) 4 socket outlets connected in radial. Indicate the colour of cables and the (ii) (8 marks) appropriate fuse. Draw the preferred graphical symbols for the following: (c) (i) play: socket-outlet; (ii) cooker control unit; (iii) link with separable contacts. (4 marks) (iv) Explain the reasons for testing a completed installation before being connected to power (d) (2 marks) supply: Name: 2 (8) three types of a.c power supply systems; (i) (5 marks) four electric power authorities in Kenya. (ii) Draw a labelled diagram of a three phase 4-wire distribution system. Include three (b) (9 marks) domestic and one industrial consumers. With the aid of a diagram, describe the polarity test of a switch with circuit dead. (c) (6 marks) State two types of conductor materials for cables. (2 marks) 3. (a) With the aid of cross-sectional diagrams, differentiate between twin core and twin (b) (6 marks) concentric cables. State four rating factors considered when determining the size of an electric cable. (c) (4 marks) A two-core copper cable supplies current to a 240 V single phase load of 20 kW at 0.8 power factor lagging. The cable is 50 metres long and each conductor has a crosssectional area of 35 mm2. Determine the voltage drop in the cable. Take resistivity of (8 marks)

1601/105

1602/105

copper as 17.5 μΩ mm.

2

Oct./Nov. 2017

4. (a) State three merits of cartridge fuses. (3 marks) Draw a labelled cross sectional diagram of a high breaking capacity fuse. (b) (5 marks) Explain the following with respect to earthing: (c) (i) earth electrode: (ii) earth continuity conductor, earthing lead. (iii) (6 marks) With the aid of a diagram, explain the operations of a voltage operated earth leakage (d) circuit breaker. (6 marks) 5 List two types of alternating current machines. (a) (2 marks) (b) (i) Draw a labelled diagram showing construction features of a D.C machine. (ii) Describe any three parts in (b)(i), (8 marks) Draw a labelled schematic diagram of capacitor start capacitor run single phase (c) induction motor. (5 marks) (d) Outline five procedures followed when dismantling an electric machine for repair. (5 marks) SECTION B Answer TWO questions from this section. Explain the following solar terminologies: 6. (a) (i) insolation; (ii) solar constant. (4 marks) (b) (i) Describe the principle of solar radiation. (ii) State three types of radiations in (b)(i). (6 marks) Outline two: (c) (i) applications of solar energy: methods of harvesting solar energy. (ii) (2 marks) With the aid of a diagram differentiate between direct and diffuse radiations. (d) (i) Explain the effect of shading on solar systems. (8 marks) (iii) 1601/105 1602/105 Turn over Oct./Nov. 2017

- 7. (a) (i) Define the term 'wiring systems'.
 - State four factors considered when selecting a wiring system for a particular solar system. (4 marks)
 - (b) Draw a labelled block diagram of a solar electric system.

(6 marks)

(c) Outline the procedure recommended when installing a solar electric system.

(6 marks)

(d) Table 1 shows results of trouble shooting of solar electric system. Complete the table.

Table 1

Problem	Cause	Remedy
Tripped circuit breakers or blown fuse		
Fluorescent lamp does not work		

(4 marks)

- 8. (a) Explain the following with respect to solar energy:
 - (i) total daily energy requirements;
 - (ii) peak-sun hours.

(4 marks)

- (b) Outline four steps followed when determining total daily energy required in (a)(i).
 (8 marks)
- (c) A solar system has daily energy requirement of 300 watt-hours. The 12 V storage battery has a maximum allowable daily depth of discharge of 0.4 and the number of storage days is 5. Determine the battery capacity for the system. (5 marks)
- (d) State three maintenance checks done on the wiring of a solar installation. (3 marks)

THIS IS THE LAST PRINTED PAGE.

1601/105 Oct/Nov. 2017

1602/105

4